



## Volt Drop Chart

Load - Lamp Wattage	Distance for 2.5mm (14AWG)	Distance for 4.0mm (12AWG)	Distance for 6.0mm (10AWG)	Distance for 10mm (8A WG)	Distance for 16mm (6A WG)	Distance for 25mm (3A WG)
20 watts	40mtr (43yds)	65mtr (70yds)	97mtr (105yds)	164mtr (177yds)	255mtr (276yds)	512mtr (555yds)
40 watts	20mtr (21.5yds)	32mtr (34.5yds)	48mtr (52yds)	81mtr (88yds)	128mtr (139yds)	258mtr (280yds)
50 watts	16mtr (17yds)	25mtr (27yds)	38mtr (41yd)	65mtr (70.5yds)	102mtr (111yds)	204mtr (221yds)
60 watts	13mtr (14yds)	20mtr (21.5yds)	32mtr (34.5yds)	54mtr (58.5yds)	85mtr (92yds)	170mtr (184yds)
70 watts	11mtr (12yds)	18mtr (19.5yds)	27mtr (29yds)	46mtr (50yds)	73mtr (79yds)	146mtr (158yds)
80 watts	10mtr (11yds)	16mtr (17yds)	24mtrs (26yds)	40mtr (43yds)	63mtr (68yds)	127mtr (137yds)
90 watts	8.5mtr (9.2yds)	14mtr (15.2yds)	21mtr (22.7yds)	35mtr (38yds)	56mtr (53yds)	113mtr (122yds)
100 watts	8mtr (8.6yds)	13mtr (14yds)	19mtr (20.5yds)	33mtr (35.7yds)	51mtr (55yds)	102mtr (110yds)
120 watts	6mtr (6.5yds)	10mtr (11yds)	16mtr (17yds)	27mtr (29yds)	42mtr (45.5yds)	85mtr (92yds)
150 watts	5.2mtr (5.6yds)	8.3mtr (9yds)	13mtr (14yds)	21mtr (23yds)	34mtr (36.8yds)	68mtr (73.6yds)
200 watts	4mtr (4.3yds)	6.5mtr (7yds)	10mtr (10.8yds)	16mtr (17.3yds)	25.5mtr (27.6yds)	51mtr (55yd)
250 watts	3.1mtr (3.3yds)	5mtr (5.4yds)	8mtr (8.6yds)	12.6mtr (13.6yds)	20.3mtr (22yds)	41mtr (44.4yds)
300 watts	2.5mtr (2.7yds)	4.2mtr (4.55yds)	6.7mtr (7.2yds)	10.7mtr (11.6yds)	16.9mtr (18.3yds)	33.8mtr (36.6yds)

(this chart is a guide only - no load output voltage of the transformer may vary)

## Metric to American Wire Gauge Conversion Chart

Metric Conductor Size	American Wire Gauge (Actual size in mm <sup>2</sup> )
1.0mm <sup>2</sup>	#18 (0.823)
1.5mm <sup>2</sup>	#16 (1.31)
2.5mm <sup>2</sup>	#14 (2.68)
4.0mm <sup>2</sup>	#12 (3.31)
6.0mm <sup>2</sup>	#10 (5.26)
10mm <sup>2</sup>	# 8 (8.37)
16mm <sup>2</sup>	# 6 (13.03)
25mm <sup>2</sup>	# 3 (26.67) *
35mm <sup>2</sup>	# 2 (33.62) *
50mm <sup>2</sup>	# 1/0 (53.49)
70mm <sup>2</sup>	# 2/0 (67.43)
95mm <sup>2</sup>	# 4/0 (85.01) *

(\*AWG size is the nearest to metric sizing).

**HUNZA**™ PURE OUTDOOR LIGHTING

**HUNZA FACTORY**  
130 Felton Mathew Ave  
Glen Innes  
Auckland 1072  
New Zealand

Ph: 64-9-528 9471  
Fax: 64-9-528 9361  
hunza@hunza.co.nz  
www.hunza.co.nz

**INTERNATIONAL CONTACTS:**  
[www.hunza.co.nz/contacts.php](http://www.hunza.co.nz/contacts.php)

Specifications may change without notice.  
Manufactured in New Zealand.

© 2009 Hunza Holdings Ltd.

Ver 1.4